



# FRM220-FTEC

## E1/T1 Cross Rate Converter

2

E1/T1 Cross Rate Converter

The FRM220-FTEC is a T1 (US Standard) /E1 (European Standard) converter and timeslot cross connect which enables conversion between one T1 signal and one E1 signal. T1 and E1 signals with framing employ u-Law and A-Law compander encoding principles respectively and encode those analog (voice) signals into 64kbps digital data. The T1 interface supports D4(SF) or ESF frame formats with B8ZS or AMI line code. The E1 interface supports CCS (PCM31) or CAS (PCM30) framing without CRC-4 and framing with CRC-4. The line coding is HDB3.

Tests and diagnostics can easily be performed from the local console interface or via Web based management of the FRM220. Diagnostics include T1 local/remote and E1 local/remote loop back. When placed in a single slot chassis and used standalone without management, the card may be configured by DIP switches.

### Feature

- Converts between T1 and E1 data and signaling
- Enable equipment to operate at T1 and E1 rates
- Supports G.802 Annex B (T1 over E1)
- Configures A-law/ $\mu$ -law and signaling conversion
- Transparent conversion at 64kbps timeslot level
- Controlled slip for buffer over or under flow
- 24 time slots of T1 Nx64 can be inserted into E1 Nx64, 30/CAS or 31/CCS timeslots

### Specifications

<b>E1 Interface</b>	Framing	CAS/PCM30 or CCS/PCM31 selectable	<b>LEDs</b>	PWR, Sys, Test, T1/E1		
	Bit rate	2.048Mbps		<b>Standard</b>	ITU-T G.703, G.704, G.706, G.823, G.824, ANSI T1.403	
	Line Code	HDB3			<b>Power</b>	12VDC
	Line Impedance	75 ohm (BNC) / 120 ohm (RJ-45)		<b>Power Consumption</b>		< 6W
	CRC check	CRC-4 enable/disable			<b>Dimensions</b>	Card: 155 x 20.8 x 88mm (D x W x H)
	Pulse amplitude	Nominal 2.37V $\pm$ 10% for 75ohm Nominal 3.00V $\pm$ 10% for 120ohm		<b>Weight</b>		130g
	Zero amplitude	$\pm$ 0.1V			<b>Temperature</b>	0 ~ 50°C (Operating), -10 ~ 70°C (Storage)
	Connector	RJ-45		<b>Humidity</b>		10 ~ 90% non-condensing
	<b>T1 Interface</b>	Framing			D4, ESF selectable	<b>Certification</b>
		Bit rate		1.544Mbps	<b>MTBF</b>	
Line Code		B8ZS / AMI				
Equalization		0 ~ 655 feet settable				
		Voice channel sample rule $\mu$ -Law				
CRC check		CRC-6 when ESF				
Line Impedance		100 ohms				
Transmit Pulse level		3.0V $\pm$ 10%,				
Receive signal level	0 ~ -10dB					
Connector	RJ-45					

### Application



### Ordering Information

Model Name	Description
FRM220-FTEC	E1/T1 Cross rate converter

**Note:** This card must use CH01M, with serial console, to configure standalone settings. For standalone SNMP management, place this card in CH02/NMC chassis.