



FMC-CH17

Simple Converter Chassis

The FMC-CH17 is a 2U high 19" 17 slots chassis. The chassis provides an economic solution in low density fiber converter installations where no management features are required. Each FMC or VDTU2A-301 converter is an independent Ethernet to fiber or Ethernet to copper media converter that may be used as a stand-alone converter or placed in the FMC-CH17 chassis. With two power supplies, the FMC-CH17 chassis supports redundant power from any of two power options. The AC supplies operate from (100-240VAC) and DC supplies operate from 36-60VDC. The built in cooling fan ensures that the temperatures in the rack remain within the tolerated working range.

Feature

- FMC-CH17, 2U, 19", 17-Slot chassis with single or dual built-in power for AC or DC
- Cross flow cooling fan built-in.
- Designed for 19" Rack mounting
- FMC units are hot swappable

Specifications

Power Input	AC : 100 ~240V or DC : 36 ~ 60V
Power Consumption	<60W
Dimensions (D x W x H)	199 x 476 x 88 mm
Weight	7.9Kg

Temperature	0 ~ 50°C (Operating), -10 ~ 70°C (Storage)
Humidity	10 ~ 90% non-condensing
Certification	CE, FCC
MTBF	65,000 hrs

Application



FMC-CH17 Front view

- FMC Option Converters
- Fast Ethernet
 - Gigabit Ethernet
 - VDSL2 LAN Extender

17-Slot



FMC-CH17 Back view



Ordering Information

Model Name	Description
FMC-CH17-AC, DC, AD, AA, DD	2U, 19", 17-Slot FMC Converter Chassis with AC, DC, AD, AA or DD power

Power Type
FMC - CH17 - □□
 Example: FMC - CH17 - DC